



NOTES

- (1) Socket to be Underwriters Laboratory (UL) listed.
- (2) May be used on single-phase overhead and underground service.
- (3) Connections for terminating service conductors shall be the lay-in type.
- (4) Service conduit to enter at point "A"
- (5) PNM will make line termination on underground service only.
- (6) No load conduits or load conductors in shaded area from front to back.
- (7) Line section shall be lockable and sealable.
- (8) Customer building numbers must be permanently painted on proper meter panels.
- (9) Meter shall be 4' - 5' 6" from finished grade.
- (10) Commercial application require bypass handle.
- (11) Metering and instrument cabinets shall not be used to house Customer-owned equipment, such as distribution panels or other equipment, nor used as a junction box/trough for the distribution of circuits.

REFERENCES

- (1) See DS-4-5.0 Underground Service Entrance System
- (2) See DM-4-11.0 Maximum Available Fault Currents

| Approved Equipment | | |
|--------------------|--------------------------|------------------------|
| Manufacturer | Item | Mfg Part # |
| Eaton | 200A OH/UG #-Gang Socket | UT*R2332BCH |
| Eaton | 200A OH/UG #-Gang Socket | UT*R2332UCH |
| Eaton | 200A OH/UG #-Gang Socket | UT*R2392UCH |
| Eaton | 200A OH/UG #-Gang Socket | UT*R2392TTCH |
| Milbank | 200A OH/UG #-Gang Socket | U125*-X-K1 |
| Milbank | 200A OH/UG #-Gang Socket | U125*-X-K3 |
| Milbank | 200A OH/UG #-Gang Socket | U125*-X-K4 |
| Siemens | 200A OH/UG #-Gang Socket | UA*716-XG |
| Siemens | 200A OH 2-Gang Socket | WP2211RJ |
| Siemens | 200A OH/UG -Gang Socket | PowerMod (Residential) |
| Square D | 200A OH/UG #-Gang Socket | MPR22-125 |
| Square D | 200A UG 2-Gang Socket | 1006737B |

* There are various catalog #'s available for # of gang socket
For ease of checking service without interruption, PNM will no longer allow ring meter sockets as of 12/01/2013.