

**NOTES**

- (1) Line conduit must be rigid galvanized, Schedule 80 PVC or IMC. Coordinate size and number of line conduits with PNM.
- (2) Main breaker may be required on the line side of any meter group sets to meet NEC, state or local codes.
- (3) All units shall be complete with sockets and breakers at the time of initial set of first meter.
- (4) Load conductors may exit either top or bottom of tenant breaker section. They shall not travel through or exit out of socket sections of modules.
- (5) All enclosures shall be securely mounted to building.
- (6) 1" placards to be used under main disconnect and adjacent to the corresponding socket on a non-removable part of the cabinet. No painted or written identification will be accepted.
- (7) Guard posts will be required in traffic areas.
- (8) Top meter shall be a maximum of 79" from finished grade. Bottom meter shall be a minimum of 30" from finish grade. Maximum of four meters per column.
- (9) PNM requires a minimum clearance of 36" minimum between front of sockets and any wall or obstruction.
- (10) All line feed sections shall be lockable and sealable by PNM.
- (11) All units shall be complete with sockets and breakers at the time of initial set of first meter.

REFERENCES

- (1) See DM-4-11.0 Maximum Available Fault Currents
- (2) See DS-7-16.10 Guard Post
- (3) See MS-2-6.0 120/208 Wye or 120/240 Delta 200A Three-Phase Four-Wire Wye or Delta Meter Socket with Bypass

Important:

Socket shall be wired phase 1-2-3 from left to right and the conductors marked as such. Each conductor phase will be identified at the weather head or padmount, and at the meter base using band-wraps of electrical tape:

One band for phase one
Two bands for phase two
Three bands for phase three
White tape is suitable for neutral conductors only.

Approved Equipment		
Manufacturer	Item	Mfg Part #
Siemens	200A OH/UG Ringless # Position	WPL4*12RJ
Siemens	200A OH/UG Ringless # Position, 600A Buss	WPL6612RJ
Siemens	200A OH/UG Ringless # Position, 800A Buss	WPL8612RJ
Siemens	200A OH/UG Ringless # Position, 1000A Buss	WPL10612RJ
Square D	200A OH/UG Ringless * Position	EZML33*225

* There are various catalog#s available for # of positions

For ease of checking service without interruption, PNM will no longer allow ring meter sockets as of 12/01/2013.

**ALBUQUERQUE
DOWNTOWN
NETWORK
ONLY**