



- NOTES**
- (1) No concrete in trough area.
 - (2) Bring conduits up flush with pad.
 - (3) Guard Posts are required in traffic areas.
 - (4) Concrete pad shall be 3000PSI concrete, level within $\pm 1/4"$ in 5' and trowel finished to provide a true plane within $1/16"$ in 5' as determined by a 5' straight edge.
 - (5) Existing grade and backfill under concrete pad shall be compacted to 95% in accordance with ASTM D1557.
 - (6) If the primary cable is direct buried contact engineer for secondary duct orientation prior to installation.
 - (7) Primary duct shall be direct buried rigid galvanized or IMC duct or concrete encased PVC duct. Customer may use schedule 40 rigid PVC minimum duct without concrete encasement provided a minimum 10' rigid galvanized or IMC duct is installed for primary at the horizontal when entering or exiting the vertical elbow at the padmounted equipment. The primary and secondary duct will be furnished and installed by the customer..
 - (8) Customer shall include a polyethylene pull string with a minimum breaking strength of 210 lbs in completed ducts for future use by PNM.
 - (9) Precast concrete pads are available through vendors.
 - (10) All secondary cables must be tagged with phase and address for tracing reasons. The secondary cables shall be marked no more than 12" above the ducts.
 - (11) Pad to be 1' thick if poured in place otherwise use 0100005824 for pre-engineered pad.
 - (12) Minimum of 1'10" x 14" to be maintained for secondary duct area to allow 8-4" secondary ducts.

REFERENCES

- (1) See DS-7-16.8 Page 1 and 2 Transformer and Switchgear Pad Foundation Preparation and Inspection
- (2) See DS-7-16.10 Guard Post
- (3) See DS-7-16.12 Minimum Working Space and Fire Safety Requirements for Transformers